

AA35 / AA60

- 3 Chanel Mixer Amplifier
- 1 Mic Input w/ Phantom Power
- 2 Stereo Line Inputs
- Dual Line Out
- Pre Out / Power In EQ Patch
- Remote and Vox Activated Mute
- Route Any Source Combination or Entire Mix Bus to Zone 2 (MOH Out)
- Special Low Cut Filter is 6dB / Octave at 400Hz and Also Bypasses Front Panel Bass Control to Allow use with Paging Horns like APX40TN and AP-15T
- UL Listed 60065
- Optional Rack Mount Kit – AARMK2-5

The AA35 35 Watt output & AA60 60 Watt output are 3 input mixer amplifiers designed for distributed business paging and background music (BGM) systems, small to medium speech privacy systems and in applications where music on hold (MOH) plus paging is required. With one microphone input and two stereo line inputs these units will accommodate a variety of input sources including paging microphones, CD players and digital music receivers. A dip switch selectable matrix allows the creation of a zone 2 mix from any or all of the input sources for music or messaging on hold applications. 25V, 70.7V, and 8Ω outputs are provided. Output power will match nicely with Atlas Sound FAP, SM, SD, and GD series loudspeakers. In fact, **in an 11' ceiling application, the AA35 will provide power for up to 117 SD72W loudspeakers tapped at .25 watts each while providing upwards of 84dB in the direct sound field at ear height!**



AA35



AA60
(Back)

Strategy Series® Amplifiers