

## 95 Series – Relays & Amplifiers, Paging Amplifiers

### 95-925 12 Volt SPDT ALARM RELAY

30/40A contacts. Current draw 120mA. Coil resistance 93 ohms DC. Can be used with Calrad 95-926 or 95-927 relay sockets.



### 95-926 SINGLE RELAY SOCKET FOR CAR ALARMS

Mates with 95-925 12V relay.




### 95-869B 6-WATT AUDIO AMPLIFIER MODULE

Solid-State Audio Amplifier Module with max 5 watt output.

#### Specifications

Power Supply Voltage ..... 12-15 V  
Frequency Response 10 to 25 KHz.  
Input Impedance ..... Low Z  
Input Sensitivity ..... 6 mv.  
Power Input..... Mono 6 W., 8Ω  
Distortion ..... 1% @ full output




Size: 2.2" x 4" x 1"

### 95-830 POWER AMPLIFIER

This power amplifier is a very versatile high fidelity amplifier and has many useful applications. A few of these are as follows: A power amplifier for Walkman or similar type of AM/FM stereo headphone radio, they can be converted into a high powered stereo system for home use. This can easily be done by connecting the headphone output from the radio to the input control of the amplifier. As a power amplifier for the auto, van, camper, trailer and boat, or as a portable system for outdoor use. A public address amplifier for both indoor and outdoor use.

#### Specifications

DC Voltage.....	12 to 15V	Input Sensitivity .....	0.6V at full output
Frequency Response .....	10 to 25 kHz	Power Output .....	Mono: 15W at 8Ω. Stereo: 6W
Input Impedance.....	Low Z	Distortion .....	1% @ full output



Size: 3" x 4" x 1"

### 95-702 15 WATT PUBLIC ADDRESS AMPLIFIER

Comes complete with microphone. Has inputs for microphone, auxiliary, phone, and microphone auxiliary. Also has built-in siren. Chassis size: 6"(W) x 2.75"(H) x 6.5"(D). 45-602 power supply sold separately for AC use.

#### Specifications:

Power Source .....	DC 12V (11-16V standard 14.4V)
Input impedance .....	Mic 200-50K ohm adaptable / Aux. 10K
Input Level .....	Mic -50dB ± 1dB / Aux. -22dB ± 1 dB (for rated output)
Output Impedance .....	4~16 ohmΩ
Power Consumption .....	Less than 3A at max. output
Siren.....	Electronic operated automatic waving type
Fog-horn.....	Electronic fog-horn
Dimensions .....	155mm(W) x 150mm(D) x 65mm(H)
Weight.....	0.78kg



Size: 6.1" x 5.9" x 2.55"

### 95-875 60 WATT PAGING AMPLIFIER

Rugged and versatile paging amplifier and mixer. One XLR mic input. Two 1/4" mono mic inputs. Three RCA auxiliary inputs. Independent controls for the microphone and auxiliary inputs allows you to mix and amplify the input signals. Front panel on/off power switch with L.E.D. indicator. Speaker outputs are screw terminals for 4Ω, 8Ω, 70 volt or 100 volt speakers. Inputs for 110 Vac or 12 Vdc. Detachable IEC electrical cord. Chassis color: Black. Includes mounting bracket.



Front

Rear

**Note:** All specifications on this page are subject to change without notice