


OLDAKER TEST LEADS & ACCESSORIES

Call 888.295.9516

Fax 888.295.9517


FerriShield, INC.
Interference Control Components

**RFI / EMI
SUPPRESSORS**




Part No.	A	B	C	D	E	IMPEDANCE IN OHMS
JB28B0010	.670	.820	.670	.290	.055	160@100MHz

JELLY BEAN SNAP : Miniature size with internal locking system cannot be reopened after snapping closed into position. Ensures that suppressor cannot be removed. Grip-lock tabs at entry/exit ports prevent longitudinal slippage. Fits .060" to .120" (1.5 to 3.0mm) diameter cable. Excellent for tight spaces and low profile applications.



Part No.	A	B	C	D	E	F	IMPEDANCE IN OHMS
TC28B0642	.785	.630	.785	.320	1.335	.195	100@100MHz
TC28B0937	1.080	.551	1.080	.449	1.630	.195	117@100MHz

CABLE CLAMP : Ferrite assembly bonded to nylon strap; Fits .320" & .449" (8.1 & 11.4mm) diameter cable. Holes are provided for screw mounting. Other sizes available upon request.



Part No.	WITHOUT ADHESIVE	A	B	C	D	E	IMPEDANCE IN OHMS
FA28B2480	FC28B2480	.800	3.180	1.125	.040	2.047	250@100MHz
FA28B3012	FC28B3012	.800	3.700	1.125	.040	2.540	286@100MHz

FLAT CABLE CLAMP : With adhesive mount. Ferrite assembly bonded to nylon mounting clamp; easily installed by peeling protective paper strip from base and pressing into place. Fits ribbon cable 1.125" (28.6mm) flat cable. Other sizes available upon request.