

---

# MUSICAL FIDELITY

---

## F25 Preamplifier

 Print This Page

### OVERVIEW

### FEATURES & BENEFITS

<b>Full remote control via infra red handset</b>	Allows simple control of volume and selection from listening position
<b>Balanced or single ended output</b>	Allows selection of optimal cable for set-up. Balanced operation improves signal quality over long cable runs
<b>Very high quality phono stage with switchable input impedance</b>	Allows use of MM or MC cartridges with switchable resistive and capacitive loading to allow perfect matching to your cartridge
<b>Switchable RIAA/IEC curves for phono input</b>	Allows choice of original RIAA curve or more recent IEC amendment to tailor the bass response to suit your system
<b>High quality Tiffany type gold phono connectors</b>	Highest sound quality with excellent mechanical contact
<b>External processor loop</b>	Allows use of processors such as surround sound units without using up the tape loop or degrading the signal with unnecessary switching
<b>Low feedback Class A circuitry</b>	Highest possible sound quality as you would expect from the F-series flagship

**Switchable balanced input** The auxiliary input can be balanced or single-ended for use with high end sources with true balanced outputs

---

## SPECIFICATIONS

**Inputs** 4 Line, Tape, Phono (MM/MC)

---

**THD** < 0.01%

---

**Frequency response** 20Hz - 20kHz + 1dB

---

**Input sensitivity** Line: 200mV  
Phono: MM 3mV, MC 300 $\mu$ V

---

**S/N ratio** Line: > -85dB  
Phono MM: > -75dB  
Phono MC: > -60dB

---

**Tape output** Dependent on input level

---

**Power consumption** 10 watts

---

**Dimensions** 480 x 120 x 340mm (W x H x D)  
Height includes feet

---

**Weight** 7.5 kgs

---

**Standard accessories** Remote control unit  
2 x batteries (SUM-4, AA, R03)  
IEC type mains lead

---