

JUNIOR SUPER SINGLE® Pump Switch

Mercury activated, wide-angle switch designed for direct control of pumps up to 1/2 HP at 120 VAC and 1 HP at 230 VAC.

This mercury activated, wide-angle pump switch provides automatic control of smaller pumps in non-potable water and sewage applications.

Although this switch is not sensitive to rotation, it is affected by turbulence and should be mounted in a non-turbulent location.



The **Junior Super Single**® pump switch is not recommended for use with motor contactors or relays because the motor contactor or relay may experience chattering. A Super Single® or Double Float® pump switch would operate more efficiently in these installations.



U.S. Patent Nos. 4,529,854 & 4,572,934

FEATURES

- Controls pumps up to 1/2 HP at 120 VAC and 1 HP at 230 VAC.
- Adjustable pumping range of 6.5 to 19 inches (16.5 to 48 cm).
- Includes standard mounting clamp and boxed packaging.
- UL Recognized for use in non-potable water and sewage.
- CSA Certified.
- Three-year limited warranty.



OPTIONS

This switch is available:

- for pump down or pump up applications as specified by part number.
- with a 120 VAC or 230 VAC piggy-back plug.
- without a plug for direct wiring in 120 VAC or 230 VAC applications.
- in standard cable lengths of 10, 15, 20, or 30 feet and 3, 5, 6, or 10 meters (longer lengths available).

SPECIFICATIONS

CABLE: flexible 16 gauge, 2 conductor (UL, CSA) SJOW, water-resistant (CPE)

FLOAT: 2.81 inch diameter x 3.42 inch long (7.14 cm x 8.68 cm), high impact, corrosion resistant, PVC housing for use in sewage and non-potable water up to 140°F (60°C)

MERCURY SWITCH: mercury-to-metal contacts, hermetically sealed in a steel capsule

ELECTRICAL:

120 VAC 50/60Hz Single Phase:

Maximum Pump Running Current:

13 amps

Maximum Pump Starting Current:

40 amps

Recommended Pump HP:

1/2 HP or less

230 VAC 50/60Hz Single Phase:

Maximum Pump Running Current:

8 amps

Maximum Pump Starting Current:

20 amps

Recommended Pump HP:

1 HP or less

NOTE: This switch must be used with pumps that provide integral thermal overload protection.

**SJE
Rhombus**

PO Box 1708, Detroit Lakes, MN 56502

1-888-DIAL-SJE • 1-218-847-1317

1-218-847-4617 Fax

email: sje@sjerhombus.com

www.sjerhombus.com