



15, 30, & 60 Watt Transformers

Atlas Sound constant-voltage line-matching transformers are designed for use with compression driver type loudspeakers. All units provide low insertion loss and cost-efficient power handling. (Transformers for cone loudspeakers are listed in on page 35).

T10 15 Watt Transformer

Primary: 8K, 4K, 2K, 1K, 670, 325, 180, 90, & 45Ω.
 25 Volt power taps: .3, .6, .9, 1.9, 3.5, 7, & 14 watts.
 70.7 Volt power taps: .65, 1.25, 2.5, 5, 7.5, & 15 watts.
 Secondary: 4, 8, & 16Ω.

T20 30 Watt Transformer

Primary: 2500, 1300, 666, 333, 167, 89, & 45Ω.
 25 Volt power taps: 1.89, 3.7, 7, & 15 watts.
 70.7-Volt power taps: 1.8, 3.7, 7.5, 15, & 30 watts.
 Secondary: 8Ω.

T18 60 Watt Transformer

Primary: 2K, 1K, 500, 250, 125, 85, and 45Ω.
 25 Volt power taps: .3, .6, 1.25, 2.5, 5, 7, & 14 watts
 70.7 Volt power taps: 2.5, 5, 10, 20, 40, & 60 watts.
 Secondary: 4, 8, & 16Ω.

Cable / Conduit Adapters

Vandal-resistant cover plates for armored cable and conduit connection are designed for use with environment-resistant, double re-entrant loudspeakers. BX Series mounts standard male threaded pipe with 14 threads per inch. Construction is cast aluminum.

Mounting Accessories

APBK Replacement Omni-Purpose® swivel bracket, gray.

FAMT-6 Mounting ring/adapter allows a 6" cone or APF Series loudspeaker to mount an 8" enclosure and/or grille.

