



## DMS-1200 Network Multi-Zone Amplifier

This amplifier provides high-powered crystal clear audio from any music source of choice. Installed as a standalone central amplifier, you get up to 8 individual zones at a very compelling price. Infuse your streaming music services and Internet radio into a DMS-1200 multi-zone system by adding the URC SNP-1 streaming network player. Stream Pandora®, Rhapsody™, SiriusXM®, vTuner Internet radio, and other services to the pool area independently without interfering with Mom's playlist in the kitchen.

### Key Features

- Eight (8) zones; expandable up to 32 zones with use of other DMS-series amplifiers
- Four (4) analog-to-digital inputs that stream to other DMS-series amplifiers
- Can be programmed off premises via the Internet, MRX-10 and future-specified URC controllers
- Receives all streams from SNP and DMS-series amplifiers
- Easy rack mounting (requires RMK-3)

### Specifications

MFS-8 or MFSPOE-8 MAC-filtering Network Switch required

Rated Output: 50 W/ch (zones 1-6), preamp level (zones 7-8), stable to 4 Ohms

Network: 10/100 Ethernet port

Control: IR (one-way), IP (2-way) control

Indicators: Power (blue LED; blinks when resetting), Network (blue LED)

Zones of Stereo Audio: Eight (six powered zones, two pre-amp only zones)

Rated Wattage per Channel: 50 W/ch @ 8 Ohms, stable to 4 Ohms

Automatic Low Volume Loudness Compensation: Installer configured for type and size of audio zone

Installer Configured EQ: Bass Boost, Treble Boost, 5-band parametric EQ

Input sensitivity: 600~2200mVp-p / 10Kohm

User Adjustable Audio Controls: Bass, Treble and Balance

Inputs: 4 stereo line inputs (all stream to all other DMS Amplifiers)

Zone 7 and 8 Preamp Output Options: Fixed / variable line level output (each with 12V trigger)

Power: AC 100~245V, 50/60Hz

Power Consumption: 3~6A

Size: 17" x 5.25" x 16" (W x H x D)

Weight: 26.70 lbs



## DMS-100 Network Single-Zone Amplifier

Add premium audio quality streams to any one area of a home with the DMS-100. This versatile single-zone network amplifier can be installed as an additional zone with a DMS-1200 system, or installed in multiples to create a customized multi-zone system. One audio input on board allows you to plug in any music source. Add additional zones of audio anywhere at any time following the same simple formula. With multiple DMS amps you can share audio sources across zones, up to 32 sources in total, all playing independently at the same time and with no audible signal degradation.

### Key Features

- 50 w/ch @ 8 ohms, stable to 4 ohms
- Preamp output for connection to local amp or receiver
- One (1) audio input streams to other DMS-series amplifiers
- Receives all streams from SNP and DMS-series amplifiers
- Can be programmed off premises via the Internet, MRX-10 and future-specified URC controllers
- Easy rack-mounting (requires RMK-1)

### Specifications

MFS-8 or MFSPOE-8 MAC-filtering Network Switch required

Rated Wattage per Channel: 50 W/ch @ 8 Ohms, stable to 4 Ohms

Network: 10/100 Ethernet port

Control: IR (one-way), IP (two-way) control

Indicators: Power (blue LED; blinks when resetting), Network (blue LED)

Zones of Stereo Audio: One (preamp and speaker output are linked)

Automatic Low Volume Loudness Compensation: Installer configured for type and size of audio zone

Installer Configured EQ: Bass Boost, Treble Boost, 5-band parametric EQ

Input sensitivity: 600~2200mVp-p / 10Kohm

User Adjustable Audio Controls: Bass, Treble and Balance

Inputs: One (1) stereo line input (streams to all other DMS Amplifiers)

Preamp Output: Configurable to fixed line level output

Power: AC 100~245V, 50/60Hz

Power Consumption: 1~2A

Size: 17" x 1.7" x 8.7" (W x H x D)

Weight: 7 lbs