Mity Box New!

Mity Box Speaker System

Mity Box - 50 Watt Speakers - Amplified - Wired/UHF Wireless PA Simple and easy to use. Designed for teachers, corporate presenters and training instructors. Three different systems in a small, elegant design.

The AmpliVox Mity Box's small speaker design is great for small venues. Full range performance in a small compact design. You get spacious sound that extends well beyond the speaker's physical size. Like all AmpliVox PA speaker systems, they are engineered for quality voice reinforcement.

 Choose between a passive speaker; a 50W amplified / wired microphone PA speaker or a 50W amplified / wired / wireless 16 channel PA design.

- The polyethylene cabinet measures 10.5"L x 7"W x 6.5"D with a weight of only 4.5 pounds.
- All speakers include a "C" shape mounting bracket for wall mounting. The two amplified speakers also include a power on/off switch and 110VAC wall adapter.

Enclosure:Sealed Type / Rotational Molded

Power Handling:50 Watts Rated Impedance:4 ohm

Frequency Response: ...50 – 20,000 Hz

Speaker Type:6 x 8 inch, full range, cone-type Input Connector:1 Spring Loaded Speaker Terminal

Enclosure Color:Black

Front View of all Speaker models

Grille:Perforated / Black





Model SS1230 – 50 W. Amplified Speaker with Wired Microphone

Amplified speaker contains a 50 watt peak audio amplifier. Use by itself or connect to the passive speaker for larger sound coverage using the ¼" Left and Right output connectors. When using as a PA you have flexibility for three microphone selections. ¼" dynamic, 3.5mm condenser or 3.5mm wireless connectors. As an amplified audio speaker, plug in any audio source, iPod / MP3 or CD player into the 3.5mm stereo connector. A 3.5mm stereo output connector is also included. Control speaker output with the separate volume control the microphone and a separate volume and tone control for the line in audio source.

Model SW1230 – 16 Channel UHF Wireless Microphone / Amplified Speaker



Model S1230 – Passive Speaker

Passive speaker connects to any audio system with spring wire terminals.

Amplifier: 50 Watts

Inputs: 1 – RCA, Audio

1 – ¼" Microphone Jack

1 – 3.5mm Line Level

1 – 12V D

Outputs: 1 – 3.5mm Line Level 1 – ¼" Jack, Speakers Controls: Volume / On / Off