CAM6.6T CAM6.6T and CAM6.6X Receivers Built-In AM/FM Tuner Home Theater Mute 12VDC Keypad Ports, 12VDC Trigger IN. Trigger IN CAM6.6X RS232 Built-In XM Interface Mute 12VDC Satellite Radio 12VDC Trigger OUT Trigger OUT **RNET Link** AC 240V IN and OUT IR Learning Window AC 110V Switch EP EP EP EP SRC2 Remote Fixed/Variable Speaker Outputs Fuse Holder Source Included Switch Line Inputs with Removable Outputs Source 1 IN **Snap Connectors** Detachable Tuner OUT Routed IR Audio Line Cord Common IR

Outputs

Specifications

CAM6.6T AM/FM Tuner

Antenna impedance AM: 300 ohm balanced

Impedance FM: 75 ohm unbalanced Sensitivity @ S/N AM: 20 dB 55dBu

FM: 30 dB 6dB max. 12dBu

Image rejection AM: 33 dB

FM: 80 dB

S/N ratio AM: 45 dB

FM: 60 dB

CAM6.6X Satellite Tuner

XM band 2332.5 - 2345 MHz XM antenna 50 ohm SMB connection

Amplifier

Frequency response 20 Hz-20 kHz +/- 0.5 dB

Watts per channel 20 watts RMS x 12 into 8 ohms

Total harmonic distortion 0.05% Signal to noise ratio 88 dB

Audio source inputs 6 (including internal tuner)

Audio zone outputs 6 speaker level (2 line level)

Max source audio input 5V peak to peak, 10k ohms Zone variable line

Audio output 5.6V peak to peak, 4 ohms @ 1 kHz

Zone fixed line

Audio output 5.6V peak to peak, 4 ohms @ 1 kHz Trigger outputs 1 common, 12VDC 100mA each

Trigger inputs 1 home theater

Frequency range AM 530 - 1710 kHz FM 87.7 - 107.9 MHz

Physical

Line

Outputs

Dimensions 17"W x 12"D x 3.5"H (43 x 30.5 x 9 cm)

Weight 18 lbs (8.1 kg) Power Supply 110 or 240 VAC

Fuse Rating 110V input; F3A H 250V

US and Canada 240V input; T1.25A H 250V Europe

UNO-S1 Smart Keypad

Dimensions 1.875"W x 1.125"D x 4.3"H (4.8 x 10.9 x 2.8 cm)

Single gang UL/CSA approved junction box

Weight 5 oz (141 g)

Power requirements 12 VDC 150mA CAT-5 connection 110 punchdown

UNO-S2 Smart Keypad

Dimensions 3.65"W x 1.125"D x 4.3"H

 $(9.2 \times 10.9 \times 2.8 \text{ cm})$ Double gang UL/CSA

approved junction box

6 oz (170 g) Weight

Power requirements 12 VDC 180mA CAT-5 connection 110 punchdown





LR 1600-0002 02/07

RRussound

5 Forbes Road, Newmarket, New Hampshire 03857 USA

603.659.5170

www.russound.com

Since 1967, innovation, quality and reliability have been the core of the Russound product tradition. Today, Russound offers everything for enjoying multiroom audio-video in your home. All audio-video distributed solutions are built to high standards and designed with the unique consideration of making products that are a pleasure to live with and enjoy.

©2007 Russound. All rights reserved. All trademarks are the property of their respective owners. Specifications are subject to change without notice Russound is not responsible for typographical errors or omissions




CAM6.6T and CAM6.6X Six-Zone AM/FM or XM Receivers



All you need to know is Russound





Music, news, sports in any room you want





Let the music begin

You enjoy it. Dance to it. Relax to it. And now, you don't even have to see it. Wherever you are, there can be music. At the touch of a button.

No more clunky radios. No more visible stereo systems. Just out-ofsight quality sound. Music from

Russound. Heard, but not seen. And designed for you.

Choose whatever music and sound you want, wherever and whenever you want to hear it. Play XM satellite radio. Listen to sports. News. A favorite CD. MP3. You decide.

Go ahead and take control over your universe. All you need to know is Russound.

Surprisingly affordable

Ready to give you hours of high-quality

It's a fact. Put simply, the CAM6.6T and CAM6.6X receivers are surprisingly affordable. For less than you might spend on a stereo system for a single room, these receivers give you a choice of music for up to six rooms.

Reliable quality

music, the Russound CAM6.6T and CAM6.6X receivers, combined with the UNO-S1 or UNO-S2

Smart Keypads, are reliable and based on award-winning technology.

RIRussound



Simplicity and style

The CAM6.6T AM/FM and the CAM6.6X XM receivers are easy to use. There are no complicated instructions. No perplexing controls. Just music where and when you want it.

Convenient, beautiful music

Imagine a continuous flow of music as you walk around your universe. Natural sound that resonates where you want it. In the kitchen. The den. The bathroom. The porch. The bedroom. The study.

Sunnier mornings. Relaxing evenings. Fun times together.

A Russound CAM6.6T modular receiver offers AM/FM radio and more. It allows you to choose up to six sources of audio that can play in six different areas of your home. In any room. At any time.

The CAM6.6X modular design receiver offers XM satellite radio, giving you even more choices of music, all with superior sonic performance. Both receivers are home improvements that fill your universe with beautiful music. It's a sound decision that enhances your lifestyle while increasing the value of your home.

Our worldwide network of custom installers have the expertise to complete the installation that's just right for you.

UNO-S1 and UNO-S2 Smart Keypads

Feature a graphically-rich display and easy-to-use keypad that shows you what's playing in real time. Using an attractive Decora-style plate available in five colors, these keypads are at home in any room.



The UNO experience is where you want it

It looks like a wall-mounted switchplate, but push the button and hear what awaits you. Beautiful music that brightens your days, anywhere in your home.

That's the UNO experience.

Small in size, yet big in performance, an UNO Smart Keypad is the size of a single switchplate. Discreetly flush-mounted, in your choice of five colors, the keypad blends with nearly every décor and lifestyle.

Virtually foolproof, UNO turns your universe into a musical one. It simplifies your home entertainment possibilities by giving you more control over your source devices. And, it adds value to your Russound lifestyle.



The Russound philosophy

RNET communications

For compatibility with other Russound multi-room

components, the CAM6.6T and CAM6.6X receivers

Server or the ST2-XM Smart Dual Tuner, to talk with

with all your Russound components. For the installa-

have RNET on board. RNET is Russound's own

communications platform that allows Russound smart components, such as the SMS3 Smart Media

one another. For you, it means ease of operation

tion specialist, RNET speeds design and system

configuration, saving time and money.

Since 1967, innovation, quality and reliable solutions have been the core of the Russound product tradition. We're inspired by our customers, our distributors and our dealers to produce the best audio/video solutions. All Russound products are built to high standards and available worldwide. Russound is proud to be named an award-winning designer, manufacturer and supplier of multi-room audio/video solutions for the home.



Visit us on the web, www.russound.com