

Halogen Sealed Beam Lamps

Ordering Code	Barcode	Watts	Volts	Base	Filament	MOL in/mm	MOD in/mm	Life
H4651	46110	50	12.8	2 Contact Lugs	C-6	4.8/121		200
H5001	46114	50	12.8	2 Contact Lugs	C-6	4.0/102	5.75/146	200
H7604	91070	50	12.8	2 MP	C-6	2.75/70	4.5/114.3	100
H7606	02464	50	12.8	2 MP	C-6	2.75/70	4.5/114.3	400 @ 14V
H7609	91077	50	12.8	2 MP	C-6	3.75/95	5.75/146	400 @ 14V
H7610	91069	50	12.8	2 MP	C-6	2.75/70	4.5/114.3	400 @ 14V
H7614	91071	50	12.8	2 MP	C-6	2.75/70	4.5/114.3	100
H7619	91078	50	12.8	2 MP	C-6	3.75/95	5.75/146	400 @ 14V
H7635	46122	50	12.8	2 MP	C-6	3.75/95	5.75/146	100
H7921-1	91088	50	12.8	2 MP	C-6	4.53/115		200 @ 14V
H7935-1	91089	50	12.8	2 MP	C-6	4.53/115		100
H9405	91100	50	12.8	2 Rt Angle Lugs	C-6	3.0/76		100
H9406	91096	50	12.8	2 Rt Angle Lugs	C-6	3.0/76		400 at 14V
H9411	91098	50	12.8	2 Rt Angle Lugs	C-6	3.0/76		400 at 14V
H9414	91101	50	12.8	2 Rt Angle Lugs	C-6	3.0/76		400 at 14V
H9420	91102	50	12.8	2 Rt Angle Lugs	C-6	3.0/76		200 at 14V
H9421	91097	50	12.8	2 Rt Angle Lugs	C-6	3.0/76		200 at 14V
H4351	46107	55	12.8	Right Angle, Plastic	C-8	4.0/102		500
H4703	91094	55	12.8	2 Contact Lugs	C-8	3.35/85		320
H4352	46109	65	12.8	Right Angle, Plastic	C-8	4.0/102		150
H4701	91095	65	12.8	2 Contact Lugs	C-8	3.35/85		150
H4656	46112	35/35	12.8	3 Contact Lugs	C-6/C-6	4.8/121		200/320
H4656CVXL	07669	35/35	12.8	3 Contact Lugs	C-6/C-6	4.8/121		200/320
H4656PVP	07655	35/35	12.8	3 Contact Lugs	C-6/C-6	4.8/121		200/320
H5006	46116	35/35	12.8	3 Contact Lugs	C-6/C-6	4.0/102	5.75/146	200/320
H6024	46118	65/35	12.8	3 Contact Lugs	C-6/C-6	5.0/127	7.0/178	150/450
H6054	46120	65/35	12.8	3 Contact Lugs	C-6/C-6	5.44/138		150/320
H6054CVXL	07666	65/35	12.8	3 Contact Lugs	C-6/C-6	5.315/136		150/320
H6054PVP	07653	65/35	12.8	3 Contact Lugs	C-6/C-6	5.44/138		150/320
H4666	46117	65/45	12.8	3 Contact Lugs	C-8/C-8	4.8/121		150/320
H4666CVXL	07755	65/45	12.8	3 Contact Lugs	C-8/C-8	4.8/121		150/320

>>Continued on page 71



H4651



H4701



H4666



H6054