

The portability and versatility of a wireless PA system are built into the PA Pro. Powerful enough to handle indoor and out-door uses for up to 150 people, it is ideal for school yards, tour groups, meetings & can be a potential lifesaver in emergencies where crowd control and communication can make the critical difference.

PA11 PA Pro Features

- Built-in carrying handle for playground use, meetings or tours
- 3.5mm AUX Input Jack.
- 3.5mm Audio Output jack.
- Rugged ABS plastic casing withstands repeated use
- Separate tone and volume controls
- 6 hour battery use with low battery indicator and unit still operates while recharging its built-in battery
- Hands-free wireless mic and belt-pack transmitter
- Lightweight transmitter comfortably worn on waist
- Internal storage space for transmitter, charger, & mic
- 6.3mm mic jack for use with a wired microphone
- 100' wireless range from transmitter to PA
- 213.750 MHz frequency for crowd management

Belt Pack Transmitter/Lapel Mic

FrequencyVHF, CrysModel PA11213.750 MPower Output10 milliWaControlsLow BatteInput Jack3.5mm miPower Requirements2 "AA" bat

Receiver / Amplifier

Frequency Model PA11 Antenna Other Features Power Output Distortion Controls

Output Speaker Power Source AC:

Battery Run Time Battery Recharge Time Safety Approval Dimensions Total Weight shipping weight VHF, Crystal controlled 213.750 MHz 10 milliWatts Low Battery LED Indicator 3.5mm mic jack 2 "AA" batteries (included)

Crystal controlled 213.750 MHz Telescoping **RF Signal, LED Power Indicator** 20 Watts, RMS <10% THD Power On / Volume, Power on LED Indicator, Tone control 3.5mm AUX Input Jack 6.3mm mic jack 3.5mm Audio Output jack 4.5" diameter, 15W @ 4 Ohms 100-240 VAC ~ 50-60 Hz Switching-type power adapter with DC 16.5V/0.9A output. Internal rechargeable battery 6 hours @ 50% duty cycle 7 hours with included wall adapter CE approved safe for school use 7.1"W x 4"D x 9.8"H 5 lbs., without batteries 7 lbs.

Warranty 1 year for use in schools, businesses, government facilities, and churches