

ProComm Converter Series *Comparison Chart*



Inputs/Outputs

	ProComm	ProComm Go
Digital Inputs	1	0
Digital Outputs	2	2
Pulse Outputs	Yes	Yes
Frequency Out	Yes	No
Alarms	Yes	No*
4-20mA Outputs	Active	Passive

*Alarm indication on display

Communication

	ProComm	ProComm Go
Hart*	Optional	No
Modbus*	Optional	No
Profibus	No	No
AMI/AMR*	Optional**	Optional
Built-In Verification	Optional	No
Data Logger	Optional	Yes

*Hart, Modbus, and AMR: only one available with ProComm only

**Available as factory add only

Accessibility

	ProComm	ProComm Go
Display	8-line graphical	128 X 64 LCD
Touchpad	6 button	No
Computer Connection	Mini USB	Mini USB
Software	MCP & ISOBIV	McGO
RS-232	No	No
RS-485	Optional	No

Compatibility

	ProComm	ProComm Go
Ultra Mag®	Yes	Yes
FPI Mag®	Yes	Yes
McMag ³⁰⁰⁰	No	Yes
Dura Mag®	No	Yes
SPI Mag™	Yes	Yes

Power Requirements

	ProComm	ProComm Go
Consumption	10W	2W
AC Input	100-240VAC	Optional 100-240VAC
DC Input	Optional 12-48VDC	Optional 10-35VDC
Battery	No	Yes
Solar Input	No	No

Environmental

	ProComm	ProComm Go
Operating Temp.	-4° to 140°F	-4° to 140°F
Ingress Protection	IP67	IP67
UL Compliance	Yes	No
CSA Compliance	Yes	No
CE Compliance	Yes	No

User Interface

	ProComm	ProComm Go
Backlit Display	Yes	No
Display Orientation	Vertical / Horizontal	Fixed
Standard Display Sunshield	Plastic Sunshield	Die-Cast Sunshield
Programming Port	Front	Side
Wall Mount	Yes	Yes
Pole Mount (Vertical and Horizontal)	Yes	Yes
Boot Cover	No	Yes