

Single Source Hubs continued

A-H4Dx



Four Zone Single Source In-wall Expansion Hub for A-H4D. Plugs into existing A-H4D hub for 4 additional zones. Requires A-PS and A-H4D. Installation requires a three-gang work box.

*Wall plates not included with keypads.

6.5" W x 3" H x 1.225" D (165 x 76 x 32 mm

Order #	Color
2000-116063	White
2000-116087	Almond
2000-117893	Bone
2000-117909	Black
2000-117916	Brown

Shipping Weight

1 lbs (.5kg)

Min. Advertised Price
\$139.00

Keypads and Accessories

A-KP2



A-BUS Amplified Keypad.* Features IR control & pass through, pre-amp outputs, L&R channel gain controls, backlit, volume and system status indicators, source selection if used with the A-H484 Multi-Source Hub.

*Wall plates not included with keypads.

1.3125" W x 2.5" H x 1.75" D (33.5 x 63.5 x 44.5 mm)



Order #	Color
2000-115905	White
2000-115929	Almond
2000-117770	Bone
2000-117794	Black
2000-117787	Brown

Shipping Weight 5oz (.14kg) Min. Advertised Price \$189.00

A-VC2



A-BUS Amplified Volume Control.* Features system status indicator, pre-amp outputs, L&R channel gain controls with 110 punchdown termination.

*Wall plates not included with keypads.

*Do not use with multi-source A-BUS Hubs. 1.3125" W x 2.5" H x 1.5" D (33.5 x 63.5 x 38.5 mm)



Order #	Color
2000-115943	White
2000-115967	Almond
2000-521201	Bone
2000-521218	Black
2000-521188	Brown

Shipping Weight
5oz (.1kg)
Min. Advertised Price
\$10900

A-LRC1



Learning/Preprogrammed Remote Control. Features: source selection and control for the A-H484 multi-source hub. Pre-programmed with most major brands of audio and video equipment, can learn IR command, works well as a stand alone home theater remote.


1.75" W x 1" H x 8.5" Length (44.5 x 25.4 x 219 mm)

Order #

2000-117053

Shipping Weight
3.5oz (.11kg)
Min. Advertised Price
\$79.00

A-KP RC



1.875" W x .875" H x 4.875" Length (48 x 22.5 x 124 mm)

Order #

2000-113970

Shipping Weight
2oz (.056kg)
Min. Advertised Price
\$44.00

A-OM



A-BUS Line Level Output Module Surface-mount device provides a fixed line-level stereo signal from a keypad port on an A-BUS hub or A-BUS-ready multiroom controller for connecting to an external amplifier or receiver. RJ-45 CAT-5 cable connection, RCA jacks for left and right audio,

IR receiver input terminals for passing IR commands from a remote to the A-BUS hub or controller.

3.33" W x 2.38" H x 1.59" D (8.4 x 6.0 x 4.0 cm)

Order # Min. Advertised \$70.00

Shipping Weight
5.6 oz (158 g)
Min. Advertised Price
\$70.00

2000-526473