



# FIREWIRE INTERFACES

Home >> Products >> Computer Products >> **FireWire Interfaces / Controllers**

## FW-1884



[Overview](#)

[Specifications](#)

[Applications](#)

[Resources](#)

[Images](#)

[Buy Now](#)

- Comprehensive mixing, automation, editing and navigation tools for DAWs
- Eight 100mm motorized touch-sensitive channel faders, one motorized touch-sensitive master fader
- Dedicated controls for pan, solo, mute and select functions on each channel; tactile control for four bands of parametric EQ
- Shortcut keys for various popular audio software applications
- Eight balanced XLR analog mic/line inputs with high quality mic preamps
- Phantom power and inserts on every channel
- 24-bit/96kHz A/D and D/A converters; full 96kHz operation on all analog I/O channels with compatible DAW software
- Eight channels of ADAT lightpipe, stereo S/PDIF inputs and outputs.
- Eight analog outputs, allowing connection of L/R and 5.1 surround matrices
- Dedicated headphone output
- Four MIDI inputs, four MIDI outputs
- Word Clock in and out jacks
- Assignable footswitch jack
- Up to 18 simultaneous inputs
- Compatible with a wide variety of popular DAW applications
- Operates as a standalone 18x2 line mixer without a computer.
- FE-8 (eight-channel sidecar) expands FW-1884 with eight additional channel control strips up to 128 channels (15 FE-8s).
- SoftLCD application simulates a "scribble strip" by displaying what each channel is controlling, see the screenshots in the column on the left
- Includes Cubase LE 48-track/96kHz recording and mixing software
- Includes GigaStudio 3 LE 64-voice streaming sampler software
- Compatible with MOTU Digital Performer, Apple Logic, Steinberg Cubase and Nuendo, and Cakewalk Sonar. Control surface compatible with Digidesign Pro Tools.
- Dimensions: 22.9"W x 5.4"H x 18.9"D
- Weight: 22.7 lbs
- Compatible with the latest Intel Macs

**FW-1884** supports the following applications as a control surface:

- Ableton Live 6.04 and higher
- Cubase 3.02 and higher
- Nuendo 3.02 and higher
- SONAR 5
- Logic Pro