












The 810B is a high-performance black burst and 1kHz audio tone generator. It outputs two composite and one s-Video (Y/C) black burst signals in NTSC or PAL formats and a 1kHz audio tone simultaneously.

FEATURES

- Output 2 composite and 1 s-Video (Y/C) black burst and 1 balanced audio 1kHz tone signals.
- Control NTSC or PAL and audio level.
- Compact Kramer TOOLS™ 3 units can be rack mounted side-by-side in a 1U rack space with the optional RK-3T rack adapter.



TECHNICAL SPECIFICATIONS

VIDEO OUTPUTS: 2 black burst on BNC connectors; 1 black burst on a 4-pin connector.

AUDIO OUTPUTS: 1kHz, 4dBu/47 Ω balanced audio on a detachable terminal

block.

CONTROL: PAL/NTSC selector switch, audio level control (trimmer).

VIDEO S/N RATIO: 62dB. LINE JITTER: 2ns.

POWER SOURCE: 12V DC, 230 mA.

DIMENSIONS: 12cm x 7.5cm x 2.5cm (4.7" x 2.95" 0.98") W, D, H.

WEIGHT: O.3kg (O.67lbs) approx.
ACCESSORIES: Power adapter.

ACCESSORIES: Power adapter.
OPTIONS: RK-3T 19" rack adapter.

