












▲ US version





◀ European version



The RC-7LC is a 5-button and one rotary knob media/room controller for multimedia rooms. It controls audio components, video components and other room facilities, such as lights and screens.

FEATURES

- 5 Back-Lit Buttons On, Off, PC, DVD, & VCR each of which can execute up to 15 commands per button.
- IR Learning Function Learn commands from any IR remote.
- 4 IR Emitters Two IR ports, each of which has two branches.
- 2 Bidirectional RS-232 Ports.
- 1 RS-485 Port.
- 4 Relay Contact Closure Ports Conveniently control other room items related to the AV system such as raising and lowering drapes, the screen or the projector.
- 1 Rotary Knob For analog volume control.
- Convenient Configuration Unit configuration via front panel.
- Wall Plate Size 2 gang EU, 1 gang US.

TECHNICAL SPECIFICATIONS

PORTS: 2 bidirectional RS-232 on terminal block connectors,

1 RS-485 on a terminal block connector, configuration jack

connector for RS-232 configuration and control. OUTPUTS: 4 relays on terminal block connectors

(36V AC or DC, 2A, 60V AC maximum on

non-inductive load); 4 (2x2) IR emitters on terminal block connectors.

POWER SOURCE: 12V DC. 155mA.

 $7.1 \text{cm} \times 4.4 \text{cm} \times 13.7 \text{cm} (2.8" \times 1.75" \times 5.39") \text{ W, D, H.}$ DIMENSIONS: WEIGHT:

O.3kg (O.67lbs) approx.

ACCESSORIES: Power supply, Kramer's Windows®-based configuration

software, configuration cable.

OPTIONS: Dual IR emitter cable, single IR emitter cable,

IR extension cable, configuration cable.

