

Specifications

PROGRAMMING

Number of fixtures: Up to 100

Fixture library: All Martin (DMX) fixtures, user-definable profiles for non-Martin fixtures, generic DMX profiles

Control: Graphical control of all fixture parameters

Visualization: Martin Show Designer-5 MC Edition 45-day trial 3D Visualizer

Macros: Pan and tilt, relative or absolute movement, shape generator with different shapes and delay styles

LightJockey Manager trigger options

PLAYBACK

Cue contains 12 sequences with global or individual fade time adjustment

Master intensity control + 8 configurable intensity groups

Manual override with direct access to all functions

Independent background cue with 5 parallel sequences

Blackout and fade out function

Go button for manual cue lists

Assignable keyboard hotkeys for faster access

Smoke control independent from programming

Follow spot function

Cue list for synchronisation with timer, digital audio or Audio CD-ROM timecode

Audio analyser for triggering sequences by audio

Function and DMX channel override via DMX IN (depending on interface type)

MINIMUM SYSTEM REQUIREMENTS

64 MB RAM

Standard PC with Pentium 200 MHz or equivalent

Monitor resolution of 800 x 600 in 16 bit colors, with small fonts

USB port for DMX interface hardware

20+ MB hard disc space

Windows XP/Vista/7 (32bit and 64bit)

RECOMMENDED

1024+ MB RAM

Fast graphic card with minimum 256MB

Note: MSD-5 MC Edition 3D visualizer requires good 3D gaming graphic card and 2

Gig RAM Minimum

Pentium 4 or faster

1024 x 768 monitor resolution, 32-bit true color

USB port for DMX interface hardware

Network card (optional)

300+ MB available hard disc space

Windows XP/Vista/7 (32bit and 64bit)

INCLUDED ITEMS

Martin LightJockey DMX Software CD

Martin USB Duo DMX Interface and cables: P/N 90703010

ACCESSORIES

2510 Controller, 110-130 V, 60 Hz: P/N 90716100

2510 Controller, 220-240 V, 50 Hz: P/N 90716000

Martin USB Duo DMX: P/N 90703010

ORDERING INFORMATION

LightJockey Kit with Martin One-Key and Martin USB Duo DMX: P/N 90702070

LightJockey (License only): P/N 39808015



The 2510 Controller is a powerful playback controller for an easy and inexpensive hardware-based control solution.

Features

- Record up to 512 DMX channels from LightJockey
- Easy playback with manual selection of sequences
- Up to 10 sub-lists of sequences
- Music input for triggering scenes
- Blackout function
- Download free pre-programmed shows for Mania SCX and Mania EFX series

Specifications

PHYSICAL

Length:	483 mm (19.0 in.)
Width:	65 mm (2.6 in.)
Height:	89 mm (3.5 in.)
Weight:	1.0 kg (2.2 lbs.)

CONTROL AND PROGRAMMING

Playback triggering options: Auto, manual and music trig with built-in microphone

Capacity, LightJockey scenes: From 247 (512 channels) to 42 325 (1 channel)

Capacity 3032 Controller scenes: 8024

Sublists of sequences: Up to 10

Instant blackout button

CONTROL/USER INTERFACE

Two-digit LED display

Menu up/down plus direct access function keys