



## WPT-01 - Wireless UHF Pendant Transmitter



The **WPT-01 Wireless UHF Pendant Transmitter** is designed to send a pre-programmed text message directly to a designated pager or LED display.

The WPT-01 can generate a Cancel or Secondary message by activating its built-in magnetic switch by swiping a magnet by its left side. The WPT-01 can generate an automated message to report low battery status.

The WPT-01 can be equipped with a "Man-Down" option that activates an automated message when the WPT-01 changes position from vertical to horizontal. This option is optimal for security applications.

This water-resistant pendant includes a pendant necklace, belt clip and a wall mount bracket for various mounting options.

### Key Features:

- **Two Programmable Messages**
- **Sends Message Directly to a Pager**
- **300' - 1,000' Range (Can be Increased by Using a Data Repeater)**
- **Transmission Indicator**
- **Built-in Magnetic Cancel Switch**
- **Long-life Single Lithium Battery**
- **Low Battery Alert**

### Options, Accessories and Complementary Products:

Part Number	Description
VSPS-03	Programming Kit
WPRP-1/WPRP-2/WPRP-5	Data Repeater
Other	Man Down Sensor

### Specifications:

Dimensions	2" x 2.3" x 0.9" (W x H x D)	Call Cancel	Internal Magnetic Switch
Weight	1.3 oz.	Signalling Time	2 - 4 Seconds
Power	Single 3V Lithium Battery	Stability	Better than 5 PPM
Color	Transparent Red	Frequency	467.8000 MHz (Additional Frequencies Available)
Operating Temperature	32° - 140°F	Paging Format	POCSAG, 512 or 1200 BPS
Humidity	0% - 90%, Non-Condensing	Channel Spacing	12.5 KHz - Narrow Band
RF Power	10 mW	Activation Codes	3 (Call, Cancel & Low Battery)
Programming	PC Based Programming Kit	Limited Warranty	One Year Parts and Labor

\*Specifications Are Subject to Change Without Notification