

CALRAD

45 Series - Power Inverters

DC to AC POWER INVERTERS

Car cigarette plug power inverters. Now you can operate most AC appliances such as camcorders, computers, fax machines and portable TVs from the DC current of your car's battery. This unit is fully portable and gives you a standard AC outlet wherever your car is. These units plug into a cigarette plug and changes your car's DC into AC by using a Modified Sine Wave. Grounded AC outlets. Units come with low battery alarm and auto shutdown.

Overload and short circuit protection. Input polarity reverse protection by fuse. High surge current capability makes it easy to start TV, motors and other inductive loads.

45-900 DC to AC POWER INVERTER 80 WATTS

Changes DC to AC power, cigarette lighter plug style. Comes with illuminated On/Off switch and single 3 prong AC outlet.

SPECIFICATIONS:

Input:.....	12 Vdc	Efficiency:.....	90%
Output:.....	115 Vac	Fuse.....	10 Amps
Continuous Power.....	80 Watts	Weight.....	.60 lbs
Peak Power:.....	150 Watts	Dimensions.....	4.5" x 2.35" x 1.37" (LxWxH)




45-901 DC to AC POWER INVERTER 100 WATTS

Comes with illuminated On/Off switch, single 3 prong AC outlet and 6 ft. cord.

SPECIFICATIONS:

Input:.....	12 Vdc	Efficiency:.....	90%
Output:.....	115 Vac	Fuse.....	20 Amps
Continuous Power.....	100 Watts	Weight.....	1.1 lbs
Peak Power:.....	200 Watts	Dimensions.....	6.9" x 2.95" x 1.57" (LxWxH)



45-902 DC to AC POWER INVERTER 150 WATTS

Comes with illuminated On/Off switch, single 3 prong AC outlet and 6 ft. cord.

SPECIFICATIONS:

Input:.....	12 Vdc	Efficiency:.....	90%
Output:.....	115 Vac	Fuse.....	20 Amps
Continuous Power.....	150 Watts	Weight.....	1.1 lbs
Peak Power:.....	300 Watts	Dimensions.....	6.1" x 2.75" x 1.57" (LxWxH)



45-903 DC to AC POWER INVERTER 300 WATTS

Comes with illuminated On/Off switch, dual 3 prong AC outlets and 6 ft. cord.

SPECIFICATIONS:

Input:.....	12Vdc	Efficiency:.....	90%
Output:.....	115Vac	Fuse.....	30 Amps
Continuous Power.....	300 Watts	Weight.....	0.8 kg
Peak Power:.....	600 Watts	Dimensions.....	5.9" x 4.13" x 1.77" (LxWxH)



45-904 DC to AC POWER INVERTER 500 WATTS

Comes with illuminated On/Off switch, three 3 prong AC outlets and 18 inch battery terminal leads for both unit and car.

SPECIFICATIONS:

Input:.....	12Vdc	Efficiency:.....	90%
Output:.....	115Vac	Fuse.....	30 Amps x 2
Continuous Power.....	500 Watts	Weight.....	1.1 kg
Peak Power:.....	1000 Watts	Dimensions.....	7.90" x 5.1" x 2.35" (LxWxH)



45-905 DC to AC POWER INVERTER 1000 WATTS

Comes with illuminated On/Off switch, three 3 prong AC outlets and 18 inch battery terminal leads for both unit and car.

SPECIFICATIONS:

Input:.....	12Vdc or 24Vdc	Efficiency:.....	90%
Output:.....	115Vac	Fuse.....	30 Amps x 3
Continuous Power.....	1000 Watts	Weight.....	1.95 kg
Peak Power:.....	2000 Watts	Dimensions.....	10.45" x 5.9" x 2.35" (LxWxH)

