

LP SERIES

5500 WATTS

Portable Generator

GENERAC[®]



Portable Propane Backup Power

LP SERIES PORTABLE GENERATOR

5500 WATTS

SMART FUEL. SMART START. SMART DESIGN.

The LP5500 is the smart choice for portable home emergency backup power, utilizing the benefits of propane to provide enough power to cover essential circuits in a home. Propane fuel is easy to use, safe to store, virtually non-toxic and has a longer shelf life with lower emissions than gasoline.



PowerDial™

PowerDial™ integrates the start, run and stop functions into one simple-to-use dial, conveniently located for quicker startup and shut-down, eliminating the search for separate controls in an emergency



CONTROL PANEL FEATURES

OUTLET COVERS

provide added protection from the environment

HOUR METER

tracks maintenance intervals

CIRCUIT BREAKERS

provide overload protection



How much power do you need?

How do you determine what size generator you need?

Sizing a portable generator is relatively easy. Check out this sample:

- 1** Choose which devices you want to power at the same time.
- 2** Record and add the running watts listed for each device that you need to power.
- 3** Record the starting watts listed for each device.
- 4** Select the one device with the highest starting watts. Add that number to the total running watts to determine the total wattage requirement.

| Device | Running Watts | Additional Starting Watts | Generator Size |
|------------------|---------------|---------------------------|--|
| Refrigerator | 700 | 2200 | Minimum starting watts for your needs ↓ 5050 starting watts |
| Microwave | 1000 | 0 | |
| Sump Pump 1/2 HP | 1050 | 2150 | |
| Lights | 100 | 0 | |
| Total | 2850 | + 2200 = | |

| | Device | Running Watts | Additional Starting Watts |
|---------------------------------|-------------------------------|---------------|---------------------------|
| Household | Coffee Maker | 1500 | - |
| | Computer with a 17" Monitor | 800 | - |
| | Electric Range - 8" Element | 2100 | - |
| | Electric Water Heater | 2000 | 1000 |
| | Garage Door Opener-1/2 HP | 875 | 2350 |
| | Microwave - 1000 Watts | 1000 | - |
| | Refrigerator/Freezer | 700 | 2200 |
| | Sump Pump 1/2 HP | 1050 | 2150 |
| | Television - 27" | 500 | - |
| | Washing Machine | 1150 | 2300 |
| | Well Pump - 1/2 HP | 1000 | 2100 |
| | Central AC - 24,000 BTU | 3800 | 4950 |
| | Furnace Fan Blower - 1/2 HP | 875 | 2300 |
| Heat Pump | 4700 | 4500 | |
| Window AC - 12,000 BTU | 3250 | 3950 | |
| Job Site | Air Compressor - 1/2 HP | 1000 | 2000 |
| | Airless Paint Sprayer- 1/3 HP | 600 | 1200 |
| | Belt Sander - 3" | 1200 | 2400 |
| | Circular Saw - 7-1/4" | 1400 | 2300 |
| | Hand Drill - 1/2" | 600 | 900 |
| | Reciprocating Saw | 960 | - |
| Recreation | Quartz Halogen Work Light | 1000 | - |
| | Table Saw, 10" | 2000 | 2000 |
| | CD / DVD Player | 100 | - |
| | Color TV - 13" | 150 | - |
| | Inflator Pump | 50 | 150 |
| Outdoor Light String | 250 | - | |
| Slow Cooker | 250 | - | |
| RV Air Conditioner (13,500 BTU) | 1500 | 700 | |

* Watts listed are approximate. Check your appliance for actual requirements. Total wattage requirements assumes intermittent starting of devices.

LP5500

PORTABLE GENERATOR



SPECIFICATIONS

| SERIES | LP55 |
|----------------------------------|--|
| Model Number | 6001 |
| Running Watts | 5500 |
| Starting Watts | 6875 |
| Engine Size | 389cc |
| Engine Type | Generac OHV |
| Low-oil Shutdown | Yes |
| Starting Method | Power Dial with Recoil Pull Start |
| Covered Outlets | Yes |
| Outlets | (2) 120v 20A 5-20R Duplex, (1) 120/240V 30A L14-30R Twist Lock |
| Fuel Tank Type and Size | 20 lb. Propane Tank or 30 lb. Propane Tank (sold separately) |
| Run Time at 50% | 4hrs 46min with 20 lb. Tank or 7hrs 9min with 30 lb. Tank |
| Handles | Single Folding |
| Wheels | 10" Solid Wheels |
| First Oil Included | Yes |
| Emission Certified | EPA - 50 States (Not city of LA), CARB |
| Warranty | 2 Yr. Limited Residential and Commercial |
| Dimensions (handle down) | 35.4" x 26.3" x 36.2" |
| Product Weight (without LP tank) | 184 |

All portable specifications and models subject to change. Please consult factory for availability.

HOME STANDBY GENERATORS

The Safe, Automatic Solution for Home Backup.

The power goes out and the generator goes on – whether you are home or away. It's that's simple. Install the #1 selling home standby generator from Generac and never again deal with extension cords or refueling in a storm. Instead, enjoy safe, automatic home protection from the inconveniences and potentially dangerous effects of power outages. There's nothing like the peace of mind a Generac automatic home standby generator can give to you and your family.



AUTOMATIC 24/7 POWER PROTECTION

Portable power since 1959

Since the original portable that started it all in 1959, Generac has continued to engineer advances in standby power for more than fifty years. Generac's product range includes power solutions from portable and automatic home standby generators to backup systems for commercial and industrial applications, all backed by an extensive nationwide service network of certified dealers. Because of our ongoing commitment to quality and innovation, Generac is the name home and business owners have come to trust.

Portable Parts and Service

Generac portable generators are supported through an extensive nationwide service network that provides parts and technical support to homeowners and contractors. For a portable generator dealer near you, visit generac.com.