



LOOP POWERED DIGITAL INDICATOR

MODEL LD1001

FEATURES:

- 3 ½ digit display
- Dual relay outputs
- DIN electrical connection
- Internal push button adjustment

INPUT:

- 4-20 mA loop powered

INTERFACE:

- DIN 43650 (Direct mount to 4-20 mA output transmitter with connector option CJ)

APPLICATIONS:

- The LD1001 plug-on display is a local pressure display with an adjustable set point for use with any 4-20 mA 2-wire transmitter.
- The LD1001 comes factory set* when ordered with an acceptable transmitter for easy field installation.
- Includes internal push buttons to manually adjust zero and span, as well as decimal placement and relay set points.



MODEL LD1001

