

# Cintel Audio and KeyKode Reader



The Cintel Audio and KeyKode Reader lets you capture professional, high quality audio and KeyKode information with images directly from film with the Cintel Scanner. You get LED illumination with advanced optics and precision mechanical adjustments along with a precision capstan and encoder that automatically corrects wow and flutter. With unique identification numbers for each film frame it is easy to correlate with corresponding video time frames.

\$3,555

#### Features

#### Equalisation

Optical audio SMPTE, Magnetic audio IEC.

# Supported KeyKode Scan Speeds

All scanner speeds.

## **LED Type**

Optical audio and KeyKode Deep RED.

#### **Supported Audio Scan Speeds**

6fps-125% chosen film rate. i.e. 24fps film frame rate has a 30fps maximum scan speed and 16mm film has a 12fps lower limit.

## **Supported Optical Audio Types**

Variable Area. Variable Density.

# Audio Sampling Rate and Bit Depth

48kHz 24 bit PCM WAV file

#### Optical Audio 35mm

Bandwidth: 40Hz-16kHz ±2dB SnR Signal to Noise Ratio: Transparent film base -65dB (measured with flat weighting). Wow and Flutter: < 0.15% (measured with IEC 386 weighting).

#### **Optical Audio 16mm**

Bandwidth: 40Hz-7kHz ±2dB SnR Signal to Noise Ratio: Transparent film base -65dB (measured with flat weighting). Wow and Flutter: < 0.3% (measured with IEC 386 weighting).

## Magnetic Audio

Engagement Pressure: 15 grams Bandwidth: 32Hz-14kHz ±2dB SnR Signal to Noise Ratio: -55dB (measured with flat weighting). Wow and Flutter: < 0.3% (measured with IEC 386 weighting).

## **Full Modulation Level**

-18dBFS

#### **Headphones Level**

-18dBu at  $50\Omega$  load (for monitoring purposes only).

# Connections

# **Preview Audio Output**


3.5mm stereo headphone jack.

## **Audio Connection**

XLR6

# Computer Interface

USB Type-C for software updates.



Power Requirements

# **Power Consumption**

Voltage 12V. Power 10W.

Ideal Film Conditions

# **Operating Temperature**

18 - 28°C

# **Relative Humidity**

Maximum 65% non-condensing.

Physical Specifications



What's Included

Cintel Audio and KeyKode Reader

Warranty

12 Month Limited Manufacturer's Warranty.

uties, but excludes sales tax and shipping costs. This website uses remarketing services to advertise on third party websites to previous visitors to our site. You can pt out at any time by changing cookie settings. Privacy Policy.			
Blackmagic Design Authorized Re	seller		

All items on this website are copyright Blackmagic Design Pty. Ltd. 2023, all rights reserved. All trademarks are property of their respective owners. MSRP includes